

Datasheet SCD40 CO₂, RH and T Sensor

- Photoacoustic CO₂ sensor technology
- Integrated temperature and humidity sensor
- Best performance-to-price ratio
- Smallest form factor: 10.1 mm x 10.1 mm x 6.5 mm
- Measurement range: 0 ppm – 40'000 ppm
- Accuracy: $\pm(50 \text{ ppm} + 5\%)$
- Fully calibrated and linearized output
- Digital interface I²C
- SMD for cost- and space-saving integration



Product Summary

The SCD40 is Sensirion's next generation miniature CO₂, RH and T sensor. This sensor builds on the photoacoustic sensing principle and Sensirion's patented PAsens® and CMOSens® technology to offer high accuracy at an unmatched price and smallest form factor. SMD assembly allows cost- and space-effective integration of the sensor combined with maximal freedom of design. Finally, ambient humidity and temperature can be measured by Sensirion's algorithm expertise through modelling and compensating of external heat sources without the need for any additional components.

CO₂ is a key indicator for indoor air quality as high levels compromise human health and productivity. Thus, the SCD40 enables smart ventilating systems in the commercial and the residential sector to regulate ventilation in the most energy-efficient and human-friendly way. Furthermore, CO₂ sensors play an essential role for indoor air quality monitoring and are therefore integrated in IAQ monitors, air purifiers, smart thermostats and similar devices.

Note that the white dust and water protection membrane on top of the sensor cap must not be removed at any time.

Block Diagram



1 Sensor Performance¹

1.1 CO₂ Sensing Performance

Parameter	Conditions	Value
CO ₂ measurement range	-	0 – 40'000 ppm
Accuracy ²	0 ppm – 5'000 ppm	± (50 ppm + 5% of reading)
Repeatability ³	0 ppm – 5'000 ppm	± 10 ppm
Response time ⁴	T _{63%}	60 s
Accuracy drift per year ⁵	400 ppm – 5'000 ppm ASC field-calibration algorithm activated or FRC field-calibration function performed.	Typical: ⁶ ± (5 ppm + 0.5 % of reading)

Table 1: SCD40 CO₂ sensor specifications

1.2 Humidity Sensing Performance⁷

Parameter	Conditions	Value
Humidity measurement range	-	0 %RH – 95 %RH
Accuracy ⁸	25°C, 0 – 95 %RH	± 5 %RH
Repeatability ³	-	± 0.3 %RH
Response time ⁴	T _{63%}	> 90 s
Accuracy drift	-	< 0.25 %RH / year

Table 2: SCD40 humidity sensor specifications

1.3 Temperature Sensing Performance⁷

Parameter	Conditions	Value
Temperature measurement range ⁹	-	- 20°C – 60°C
Accuracy ^{7 10}	0 – 50°C	± (0.8°C + 0.023 × (T [°C] – 25°C))
Repeatability ³	-	± 0.1°C
Response time ⁴	T _{63%}	> 90 s
Accuracy drift	-	< 0.03 °C / year

Table 3: SCD40 temperature sensor specifications

¹ Default conditions of T = 25°C, humidity = 50 %RH, p = 1013 mbar.

² Deviation to a high-precision reference. Accuracy is fulfilled by > 90% of the sensors after calibration. Rough handling, shipping and soldering reduces the accuracy of the sensor. Full accuracy is restored with FRC or ASC recalibration features. Accuracy is based on tests with gas mixtures having a tolerance of ± 1.5%.

³ RMS error of consecutive measurements at constant conditions. Repeatability is fulfilled by > 90% of the sensors.

⁴ Time for achieving 63% of a respective step function. Response time depends on the operating mode, design-in and environment of the sensor in the final application. The specified response time represents ideal design-in situation and high performance mode operation.

⁵ For proper function of ASC field-calibration algorithm SCD40 has to be exposed to air with CO₂ concentration 400 ppm regularly.

⁶ Typical value if operated in normal RH/T operating range, see section 2.1. Maximum value is ± (5 ppm + 2 % of reading). Higher drift values might occur if the sensor is not handled according to its handling instructions.

⁷ Design-in of the SCD40 in final application and the environment impacts the accuracy of the RH/T sensor. Heat sources have to be considered for optimal performance.

Please use integrated on-board RH/T compensation algorithm to account for the actual design-in.

⁸ Deviation to a high-precision reference. Accuracy is fulfilled by > 90% of the sensors after calibration.

⁹ RH/T sensor component is capable of measuring up to T = 120°C. However, measuring at T > 70°C might result in permanent damage of the sensor module.

¹⁰ Best temperature accuracy is realized when SCD40 is operated in a low power mode.

2 Electrical Specifications

Parameter	Conditions	Value
Average current ¹¹	High performance mode, VDD=3.3 V / 5 V Low power mode, VDD=3.3 V / 5 V Ultra low power mode, VDD=3.3 V / 5V	< 60 mA / < 40 mA < 12 mA / < 8 mA < 1.5 mA / < 1 mA
Max. current ¹²	During measurement, VDD=3.3 V / 5 V	170 mA / 115 mA
DC supply voltage (V _{ddmin} - V _{ddmax}) ¹³	Min. and max. criteria to operate SCD40	2.4 – 5.5 V
Interface	-	I ² C
Input high level voltage (V _{IH})	Min. and max. criteria to operate SCD40	0.7 x VDD – 1 x VDD
Input low level voltage (V _{IL})	Min. and max. criteria to operate SCD40	-0.5 x VDD – 0.3 x VDD
Output low level voltage (V _{OL})	3 mA sink current	0.66 V

Table 4 SCD40 electrical specifications

2.1 Operation Conditions, Lifetime and Maximum Ratings

Parameter	Conditions	Value
Temperature operating conditions		-20 – 60°C
Humidity operating conditions ¹⁴	Non-condensing.	0 – 95 %RH
DC supply voltage	Exceeding specified range will result in damage of the sensor.	- 0.3 V – 6.0V
Max voltage on pins SDA, SCL, GND	Exceeding specified range will result in damage of the sensor.	-0.3 to VDD+0.3
Input current on pins SDA, SCL, GND	Exceeding specified range will result in damage of the sensor.	+/- 100 mA
Storage temperature conditions	Exceeding specified range will result in damage of the sensor.	- 40°C – 70°C
ESD HBM		2 kV
ESD CDM		500 V
Maintenance Interval	Maintenance free when ASC field-calibration algorithm ¹⁵ is used.	None
Sensor lifetime	-	> 10 years

Table 5: SCD40 operation conditions, lifetime and maximum ratings

¹¹ Average current including idle state and processing.

¹² Power supply should be designed with respect to maximum current.

¹³ FRC must be applied to engineering samples that are not operated at 3.3 V to realize full accuracy.

¹⁴ Operating the SCD40 at a relative humidity lower than 10 % can result in compromised accuracy

¹⁵ For proper function of ASC field-calibration algorithm SCD40 has to be exposed to air with 400 ppm regularly.

3 Interface Specifications

The SCD40 comes in an LGA package, see Table 6.

Name	Comments
VDD	Supply voltage
VDDH	Supply voltage, IR source
GND	Ground contact
SDA	Serial data, bidirectional
SCL	Serial clock
DNC	Do not connect, pads must be soldered to a floating pad on the customer PCB

Table 6 Pin assignment (top view).




Figure 2: SCD40 Footprint (top view): landing pads (a), soldermask (b) and solderpaste (c).

SCL is used to synchronize the communication between the microcontroller and the sensor. The SDA pin is used to transfer data to and from the sensor. For safe communication, the timing specifications defined in the I²C manual¹⁶ must be met. Both SCL and SDA lines should be connected to external pull-up resistors. To avoid signal contention, the microcontroller must only drive SDA and SCL low. The external pull-up resistors (e.g. $R_p = 10\text{ k}\Omega$) are required to pull the signal high. For dimensioning resistor sizes please take bus capacity and communication frequency into account (see for example Section 7.1 of NXP's I²C Manual for more details¹⁶). It should be noted that pull-up resistors may be included in I/O circuits of microcontrollers.

¹⁶ http://www.nxp.com/documents/user_manual/UM10204.pdf




Figure 3: Typical application circuit (for better clarity in the image, the positioning of the pins does not reflect the positions on the real sensor). VDD and VDDH must be connected to each other close to the sensor on the customer PCB.

1 Important Notices

a. Warning, Personal Injury

Do not use this product as safety or emergency stop devices or in any other application where failure of the product could result in personal injury. Do not use this product for applications other than its intended and authorized use. Before installing, handling, using or servicing this product, please consult the data sheet and application notes. Failure to comply with these instructions could result in death or serious injury.

If the Buyer shall purchase or use SENSIRION products for any unintended or unauthorized application, Buyer shall defend, indemnify and hold harmless SENSIRION and its officers, employees, subsidiaries, affiliates and distributors against all claims, costs, damages and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if SENSIRION shall be allegedly negligent with respect to the design or the manufacture of the product.

b. ESD Precautions

The inherent design of this component causes it to be sensitive to electrostatic discharge (ESD). To prevent ESD-induced damage and/or degradation, take customary and statutory ESD precautions when handling this product. See application note "ESD, Latchup and EMC" for more information.

c. Warranty

SENSIRION warrants solely to the original purchaser of this product for a period of 12 months (one year) from the date of delivery that this product shall be of the quality, material and workmanship defined in SENSIRION's published specifications of the product. Within such period, if proven to be defective, SENSIRION shall repair and/or replace this product, in SENSIRION's discretion, free of charge to the Buyer, provided that: notice in writing describing the defects shall be given to SENSIRION within fourteen (14) days after their appearance; such defects shall be found, to SENSIRION's reasonable satisfaction, to have arisen from SENSIRION's faulty design, material, or workmanship; the defective product shall be returned to SENSIRION's factory at the Buyer's expense; and the warranty period for any repaired or replaced product shall be limited to the unexpired portion of the original period.

This warranty does not apply to any equipment which has not been installed and used within the specifications recommended by SENSIRION for the intended and proper use of the equipment. EXCEPT FOR THE WARRANTIES EXPRESSLY SET FORTH HEREIN, SENSIRION MAKES NO WARRANTIES, EITHER EXPRESS OR IMPLIED, WITH RESPECT TO THE PRODUCT. ANY AND ALL WARRANTIES, INCLUDING WITHOUT LIMITATION, WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE, ARE EXPRESSLY EXCLUDED AND DECLINED.

SENSIRION is only liable for defects of this product arising under the conditions of operation provided for in the data sheet and proper use of the goods. SENSIRION explicitly disclaims all warranties, express or implied, for any period during which the goods are operated or stored not in accordance with the technical specifications.

SENSIRION does not assume any liability arising out of any application or use of any product or circuit and specifically disclaims any and all liability, including without limitation consequential or incidental damages. All operating parameters, including without limitation recommended parameters, must be validated for each customer's applications by customer's technical experts. Recommended parameters can and do vary in different applications.

SENSIRION reserves the right, without further notice, (i) to change the product specifications and/or the information in this document and (ii) to improve reliability, functions and design of this product.

Copyright© 2019, by SENSIRION.

CMOSens® is a trademark of Sensirion

All rights reserved

4 Headquarters and Subsidiaries

Sensirion AG

Laubisruetistr. 50
CH-8712 Staefa ZH
Switzerland

phone: +41 44 306 40 00
fax: +41 44 306 40 30
info@sensirion.com
www.sensirion.com

Sensirion Taiwan Co. Ltd

phone: +886 3 5506701
info@sensirion.com
www.sensirion.com

Sensirion Inc., USA

phone: +1 312 690 5858
info-us@sensirion.com
www.sensirion.com

Sensirion Japan Co. Ltd.

phone: +81 3 3444 4940
info-jp@sensirion.com
www.sensirion.co.jp

Sensirion Korea Co. Ltd.

phone: +82 31 337 7700~3
info-kr@sensirion.com
www.sensirion.co.kr

Sensirion China Co. Ltd.

phone: +86 755 8252 1501
info-cn@sensirion.com
www.sensirion.com.cn

To find your local representative, please visit www.sensirion.com/distributors